

Waveguide to Coax Adapters

NWCA-1'+NF-R WR-137 to N female, Right angle

Features: * Low VSWR

Applications: * Wireless

* Transmitter * Laboratory Test

* Radar

Electrical

Frequency: 5.37~8.17GHz VSWR: 1.2 max.

Mechanical

RF Connectors: N female

Interface: WR-137 Flange: FDP70 Material: Aluminum

Environmental


Temperature: -20~+65°C


How To Order


NWCA-137-NF-R

Customization is available upon request.

Outline Drawings







Unit: mm [in]

Tolerance: ±0.2mm [±0.008in]